

Plate Processor 125

Maintenance Chart

OPERATION	SECTION	Developer	Wash	Gum	Dryer	Cooler	Transport	Cleaning Time
1. Check the replenisher container.		Daily		Daily				~ 2 min.
2. Check the waste container.		Daily						~ 2 min.
3. Safety check of the mechanical components.		Daily	Daily	Daily	Daily			~ 5 min.
4. Clean the transport rollers from residues.		Daily	Daily	Daily	Daily			~ 5 min.
5. Check the developer level.		Daily						~ 5 min.
6. Change the water and clean the section.			Daily ²⁾					~ 10 min.
7. Change the chemistry/filter(s).		1)						~ 30 min.
8. Main cleaning: Dev ³⁾ a. Clean all rollers and guides. b. Clean the tanks with with the "PROCESSOR CLEANER". c. Clean the spray tubes with brush. d. Clean the tubes and drain with back flush.		By chemistry change						~ 1 hour
9. Main cleaning: Wash ³⁾ a. Clean the brush roller. b. Clean the tank with the "PROCESSOR CLEANER". c. Clean the tubes and drain with back flush.			By chemistry change					~ 1 hour
10. Main cleaning: Gum ⁴⁾ a. Flush the gum pumps and solenoid. ⁴⁾ b. Clean the rollers. c. Clean the tank with the "PROCESSOR CLEANER". ⁴⁾				By chemistry change				~ 1 hour
11. Clean the circulation pumps. ⁵⁾		Every 3 months	Every 3 months					~ 5 min.
12. Clean the replenisher pumps. ⁵⁾		Every 3 months		Every 3 months				~ 15 min.
13. Check the water level, fill up if necessary.						Every 2 months		~ 5 min.
14. Check the chain tensions.							5)	~ 10 min.

¹⁾ Change of chemistry/filter(s) is based on the type of chemistry.

²⁾ Machine with water circulation system built in.

³⁾ See the cleaning instructions in the User's Manual.

⁴⁾ Use lukewarm water.

⁵⁾ See the instructions in the processor's Service Manual.

Chemistry type: _____

Chemistry change: _____ m²

Filter change: _____ m²